

Features



RGB+CCT 16 Millions of colors to choose



Color temperature 2700K~6500K



Dim brightness/ Saturation



2.4G RF wireless transmission technology



Signal transmitting & Modes synchronization



Remote control Control distance 30m



Smartphone APP control (2.4GHz gateway is needed)



Support third party voice control (2.4GHz gateway is needed)

25W RGB+CCT LED Downlight

Model No.: FUT060

Input Voltage: AC100~240V 50/60Hz

Power: 25W

Working Temp.: -20~60°C CRI: >80 PF: >0.5

Color Temperature: 2700K~6500K

Luminous Flux: 2000LM Light Efficiency: 80LM/W Lifespan: 50000 hours Beam Angle: 120° RF: 2 4GHz

Control Distance: 30m

Material: ALuminum+PC Cover

Product Weight: 855g



Power: 9W

Working Temp.: -20~60°C CRI: >80 PF: >0.5

Color Temperature: 2700K~6500K


Luminous Flux: 720LM Light Efficiency: 80LM/W Lifespan: 50000 hours Beam Angle: 120°

RF: 2.4GHz


Control Distance: 30m

Material: ALuminum+PC Cover

Product Weight: 200g



Hole Size: ø200-210mm



Hole Size: ø110~125mm

RGB+CCT LED Downlight Model No.: FUT060-FUT069

9W RGB+CCT LED Ceiling Spotlight

Model No.: FUT062

Input Voltage: AC100~240V 50/60Hz

Power: 9W

Working Temp.: -20~60°C CRI: >80 PF: >0.5

Color Temperature: 2700K~6500K

Luminous Flux: 700LM Light Efficiency: 80LM/W Lifespan: 50000 hours Beam Angle: 15°

BF: 2.4GHz

Control Distance: 30m

Material: ALuminum+PC Cover

Product Weight: 320g



6W RGB+CCT LED Waterproof Downlight

Model No.: FUT063

Input Voltage: AC100~240V 50/60Hz

Power: 6W

Working Temp.: -20~60°C

CRI: >80 PF: >0.5 Color Temperature: 2700K~6500K

Luminous Flux: 500LM

Light Efficiency: 80LM/W Lifespan: 50000 hours Beam Angle: 120°

BF: 2.4GHz

Control Distance: 30m

Material: Al uminum+PC Cover

Product Weight: 267g



9W RGB+CCT Square LED Downlight

Model No.: FUT064

Input Voltage: AC100~240V 50/60Hz

Power: 9W

Working Temp.: -20~60°C CRI: >80 PF: >0.5

Color Temperature: 2700K~6500K


Luminous Flux: 720LM Light Efficiency: 80LM/W Lifespan: 50000 hours Beam Angle: 120°

RF: 2.4GHz

Control Distance: 30m

Material: ALuminum+PC Cover

Product Weight: 240g



18W RGB+CCT LED Downlight

Model No.: FUT065

Input Voltage: AC100~240V 50/60Hz

Power: 18W

Working Temp.: -20~60°C

CRI: >80 PF: >0.5

Color Temperature: 2700K~6500K

Light Efficiency: 85LM/W

Lifespan: 50000 hours

Beam Angle: 120°

BF: 2.4GHz

Control Distance: 30m

Material: Al uminum+PC Cover

Product Weight: 410g



Hole Size: ø150~160mm

12W RGB+CCT LED Downlight

Model No.: FUT066

Input Voltage: AC100~240V 50/60Hz

Power: 12W

Working Temp.: -20~60°C CRI: >80 PF: >0.5

Color Temperature: 2700K~6500K


Luminous Flux: 1100LM Light Efficiency: 88LM/W Lifespan: 50000 hours Beam Angle: 120°

RF: 2 4GHz

Control Distance: 30m

Material: ALuminum+PC Cover

Product Weight: 320a



Hole Size: ø145~150mm

6W RGB+CCT LED Downlight

Model No.: FUT068

Input Voltage: AC100~240V 50/60Hz

Power: 6W

Working Temp.: -20~60°C

Color Temperature: 2700K~6500K


Luminous Flux: 600LM Light Efficiency: 85LM/W Lifespan: 50000 hours Beam Angle: 120°

RF: 2.4GHz

Control Distance: 30m

Material: ALuminum+PC Cover

Product Weight: 160a



Hole Size: ø90~95mm

15W RGB+CCT LED Downlight

Model No.: FUT069

Input Voltage: AC100~240V 50/60Hz

Power: 15W

Working Temp.: -20~60°C CRI: >80 PF: >0.5

Color Temperature: 2700K~6500K


Luminous Flux: 1200LM Light Efficiency: 80LM/W Lifespan: 50000 hours Beam Angle: 120°

RF: 2.4GHz

Control Distance: 30m


Material: Aluminum+PC Cover


Product Weight: 640a




Instructions

- Please open the hole on the ceiling according of Diagram 1. (For the size of the hole, please refer to the parameters of the corresponding model.)
- Connect the driver properly according to the wire connection Diagram 2. And then put the driver and wire into the ceiling from the hole.
- Push in the two spring elements, make sure that they are deployed and anchored on the back of the ceiling Diagram 3 and 4.








Link/Unlink

Compatible with these remote controls (Purchased separately)







Lighting can be working after linking with remote; for more details, pls read the remote instruction.

Dynamic Mode Sheet


Number	Dynamic Mode	Brightness / Saturation / Speed
1	Mardi Gras	
2	Automatic color change	
3	Sam	
4	Gemstone	
5	Twilight	Adjustable
6	American	
7	Fat Tuesday	
8	Party	
9	Slow Color Splash	

Signal transmitting

One Downlight can transmit the signals from the remote control to another Downlight within 30m, as long as there is a Downlight within 30m, the remote control distance can be limitless.

Modes synchronization

Different Downlight can work synchronously when they are started at different times, controlled by the same remote, under same dynamic mode and within 30m distance.



Attention

- When install the lighting fixtures, pls switch off the power to make sure the safty.
- Please check whether the input voltage supply is in accordance with the lighting fixtures.
- Non-professional user cannot dismantle the lighting fixtures directly, otherwise, it may cause fire and electric shock.
- Please do not use lighting fixtures around the mental area and high magnetic field, otherwise, it will badly affect the control distance.



Made in China